

Flexible Button Programming for SBX-IP 320

1. Press TRANS/PGM.
2. Press the flexible button to be programmed.
3. Enter the applicable feature code from the following table.
4. Press HOLD/SAVE to save the setting.

Numbering Plan the 24-button Digital Phone			
Account Code	PGM + 80	Record Page MSG	PGM + 65
Alarm Reset	565	Record User Greeting	PGM + 61
Auth. Code Change	PGM + 32	Register Station Name	PGM + 74
Auth. Code Register	PGM + 31	Record User Greeting	PGM + 61
Background Music	PGM + 73	Register Station Name	PGM + 74
Call Log	PGM + 57	REDIAL button	TRANS + 97
Call Park	601-608	Ring Answer Mode	PGM + 12
Camp-On	PGM + 85	Ring Type	PGM + 11
COS Down	PGM + 21	Set Customer MSG	PGM + 52
COS Restore	PGM + 22	Set Pre-selected MSG	PGM + 51
Direct Station Select	100-131	Set Wake-up Time	PGM + 41
Erase Page MSG	PGM + 67	Speakerphone/Headset	PGM + 75
Erase User Greeting	PGM + 66	Two way recording	PGM + 54
Group Call PickUp	PGM + 71	Universal Night Answer	569
H-T-P	PGM + 12	Wake-up Disable	PGM + 42
Headset Ring Mode	PGM + 76	Walking COS	PGM + 23
Hunt Group	620-629	Outside Line Access	
ICM Hold	PGM + 83	Group	801-808
LCD Display Language	PGM + 71	Group access	9
Listen Station Number	PGM + 63	Individual Line Access	8801-8812
Listen Station Status	PGM + 64	Speed Dial	
Listen Time & Date	PGM + 62	Station speed dial	SPEED + 000-099
LOOP button	PGM + 84	System speed dial	SPEED + 2000-2449
MPB Version Display	PGM + 72	Ring Answer Mode	PGM + 12

If you have any questions please feel free to call us @ 303-688-6191